



- Three button keypad simplifies the user interface
- 8 Locating Modes: the multi-channel processor allows for simultaneous field detection from a multiple antenna array ensuring accuracy
- Transmits 2 frequencies at the same time
- Customizable frequencies and operational modes
- Automatic Impedance Matching Technology: maximizes your transmission range while minimizing power consumption
- Remotely controls your transmitter from the receiver to more than 400 meters (437 yards)
- High-Contrast LCD Interface with Back light: guides the operator to the target location by providing all relevant data including continuous depth, current measurement, signal strength, and directional arrows
- Constant Depth & Current Measurement: real time updates on line depth and signal condition

Frequency range: 512Hz to 200kHz

Channels: 640Hz, 512Hz, 815Hz, 8.192 kHz & 32.768kHz

Power: 50env & 60env, Radio Frequency;
Rectified CP 50Hz & Rectified CP 60Hz

Antennas: Simultaneous peak/null (dual horizontal antennas & vertical antenna), pin-point peak (dual horizontal antennas), directional guidance, peak (single horizontal antenna) & null (single vertical antenna)

Display: Indicators back-lit segmented LCD bar graph, battery condition, continuous mode signal strength, depth measurement, line orientation, left/right line guidance, operating mode, volume level & function indicators

Audio Indication: Variable pitch & Live Sound. 4 volume selections including mute.